JRiver Media Center 에서 X6-시리즈 셋팅하기 (21 버전 기준)

- 1. Windows에서 저희 제품을 사용하기 위해서는 Windows용 USB 2.0드라이버를 설치하여 야 합니다. <u>www.jineung.co.kr</u> 에서 제품에 해당하는 드라이버를 다운 받아 설치합니다.
- 2. JRiver Media Center를 실행합니다.
- 3. Menu 바에서 Tools를 클릭하면 생기는 창에서 Options를 선택합니다.



4. Options 창에서



- Audio Device아래 선택창에서 JAVS HIFI AUDIO ASIO Driver [ASIO] 선택
- Device Settings...에서 아래 그림과 같이 Output에서 DSD bitstream in DoP format을 선택하면 DoP방식으로 선택하지 않으면 Native 방식으로 재생됩니다. 다음 OK를 눌러 저장합니다.

JAVS HIFI AUDIO ASIO Driver [ASIO]		
Device Channel offset:	0 Channel offset determines which outputs to use on the selected device. Try different values (0, 2, 4, etc.	Buffering 50 milliseconds (recommended) Image: Use large hardware buffers (recommended to prevent stutter)
Channel swap:) until the audio is routed to the desired output. None	NOTE: Increasing buttering makes playback more skip resistant, but also increases latency (the time it takes for pause, seek, volume, DSP, etc. to take effect).
ASIO device names do not always match Windows device names. Please select the corresponding Windows device for volume control.		Open Driver Control Panel Device uses only most significant 24-bits (Lynx, etc.)
Volume device:	(Automatically try to choose at playback time)	OK Cancel

- Bitstreaming : 을 클릭하고 DSD를 선택합니다. OK 누르면 셋팅 완료됩니다.

